

尺寸	80*80mm
纸张	
工艺	

正面



Porch Wall Lamp User Guide V1.0  
Setting up your LifeSmart Porch Wall Lamp  
Model. LS181

### PRODUCT INTRODUCTION

LifeSmart Porch Wall Lamp defines a new generation of wall lamps by integrating motion detection and illuminance detection together into one device. Combined with the LifeSmart Smart Station, the lamp can be triggered ON/OFF by detecting motion and illuminance, so it may realize light ON when people coming, light ON when getting dark and many other smart control scenes.

### IN YOUR PACKAGE

Porch Wall Lamp 1    User Guide 1    Accessories 1



### SPECIFICATIONS

Size	132.6*102.7*110.0mm
Material	PC
Power Consumption	10W
Beam Angle	15~120° (Adjustable)
CCT	2700K/3000K/4000K/5000K/5700K
Operating Voltage	100-240V AC, 50/60Hz
PIR Detection Range	10m
PIR Detection Angle	120°
LED type	SMD LED
Lumen (±5%)	700~800lm
Protection Class	IP65
Communication Protocol	CoSS
Communication Distance	200m (Open field)

### INSTALLATION

**Notice:** Porch Wall Lamp installation involves strong current operation, please contact electrician to operate!

Take off the base from lamp body.



### INSTALLATION

Fix the base on the wall using screws and let the wire get through the hole of the base.



### INSTALLATION

Connect the wires within the base respectively according to the illustration.



L = BROWN  
 N = BLUE  
 PE = YELLOW-GREEN

反面

### INSTALLATION

Connect the wire between base and lamp body, then install lamp body back with the base and using screws to fix.



### INSTALLATION

The beam angle can be adjusted by rotating the plate to meet your requirement.



### SET UP

**LifeSmart's Porch Wall Lamp needs to be paired with Smart Station to join the smart system.**

- After configuration of Smart Station, click "+" on the app home page, then click "Add Device", select "Porch Wall Lamp", enter pairing mode.
- Follow the instruction on the app to finish pairing.
- If a time-out error occurs, please repeat step 1-3 until it's successfully paired.
- Porch Wall Lamp has features such as timer turn on/off and interaction with other smart devices. Please follow the instructions on the app to discover.

### WARRANTY DESCRIPTION

Thank you for purchasing this LifeSmart product. In order to protect your rights, please read the following content carefully: The warranty period of our company's products is one year from the date of purchase or longer if local laws impose a longer minimum term, in which case the minimum term is the warranty period. During the warranty period, any faults caused by the product itself or for quality problems that arise under normal usage, LifeSmart will provide a free replacement.

**User support e-mail address**  
**support@lifsmart.com**  
**Website**  
**www.lifsmart.com**



Manufacturer: Hangzhou LifeSmart Technology Co., Ltd.  
 Address: 10-11th Floor, Building A, SUPCON Information, 352 Binkang Road, Binjiang District, Hangzhou, Zhejiang, CHN

### ATTENTION

**The following conditions are not covered by the warranty:**

- Product failure or damage caused by installation, use, and maintenance that is not in accordance with the product instructions;
- Products beyond the warranty period;
- Products that have the barcode tampered with or removed;
- Devices that have been tampered with or customized outside of LifeSmart Terms Of Service as on the LifeSmart App and website;
- User-caused damage, such as inappropriate voltage input, high temperature, accidental spillage, physical damage, etc;
- Product failure or damage caused by force majeure such as earthquakes, fires, or floods;
- Product failure or damage caused by other problems except the product itself.

### DECLARATION

LifeSmart is a trademark of Hangzhou LifeSmart Technology Co., Ltd. As for the trademarks, product logos and product names from other companies presented within this manual, they are possessed by their own right holders. Without our written permission, no entity or individual shall extract, copy or disseminate in part or the whole of the manual contents in any form. Due to product version upgrades or other reasons, content of this manual may change. Our company reserves the right to change the contents of this manual without any notice.

This manual is used only for instructional purposes. We strive to provide accurate information in this manual, but we are not able to ensure that the content of this manual is current. Statements, information and advice in this manual do not constitute any expressed or implied assurance. Updated manuals are available on our website at [www.lifsmart.com](http://www.lifsmart.com) or by contacting our team.

### DECLARATION

**DECLARATION OF CONFORMITY**

Hereby, LifeSmart declares that the radio equipment type is in compliance with Directive 2014/53/EU. The full text of the EU declaration of conformity is available at the following internet address: <http://global.lifsmart.com/ce/docs/>



**Notice: This device may be used in each member state in EU.**

Facebook: lifsmarthome    Twitter: lifsmarthome  
 Copyright © 2019 LifeSmart Inc. All Rights Reserved. P/N: 88002370 A1